

25.3 KABLOLARIN TS SEMBOLLERİ VE VDE KARŞILIKLARI SON DURUM

RUMUZLAR			STANDARTLAR			
ESKİ TS	GEÇERLİ TS	VDE	ESKİ TS	GEÇERLİ TS	HARMONİZE	VDE
NV	H05V-U	H05V-U	833	9758	HD.21.3 S3	0281
NV	H07V-U	H07V-U	833	9758	HD.21.3 S3	0281
NV	H05V-R	H05V-R	833	9758	HD.21.3 S3	0281
NV-b	H05V-K	H05V-K	833	9758	HD.21.3 S3	0281
NV-b	H07V-K	H07V-K	833	9758	HD.21.3 S3	0281
NV-y	H03VH-H	H03VH-H	833	9760	HD.21.5 S3	0250
NVV	NVV	NYM	833	9759	HD.21.4 S3	0281
FVV	H03VV-F	H03VV-F	936	9760	HD.21.5 S3	0281
FVV-y	H03VVH2-F	H03VVH2-F	936	9760	HD.21.5 S3	0281
FVV-n	H05VV-F	H05VV-F	936	9760	HD.21.5 S3	0281
	YVV	NYV		11178		0276
	YVMV	NYCY		11178		0276
	YVOV	NYRGY		11178		0271
	YVŞV	NYFGY		11178		0276
	YVŞV	NYFGY		11178		0271
	YE3V	2XY		11178		0276
	YE3MV	2XCX		11178		0276
	YE3ŞV	2XFGY		11178		0271
	YE3SV	2XSY		11178		
	YE3SHŞV	2XSEYFGY		11178		
	YE3SV	N2XSY		11178		0276
	YE3SHŞV	N2XSEYFGY		11178		0276
	YE3SV	2XSY				
	YE3SHŞV	2XSEYFGY				
	YE3SV	2XSY		2742/TSEK		
	YE3SŞV	2XSEYFGY		2742/TSEK		
		LSPYY				0245
		LSPYCY				0245
		(N) LSY				0245
		(N) LSCY				0245
	H0VV5-F	H05VV5-F			HD 21.13.S1	
	H05VVC4V5-K	H05VVC4V5-K			HD 21.13.S1	
FLL-nvg	H0RN-F	H05RN-F	936	9765	HD 22.4 S3	0282
FLL-n	H05RR-F	H05RR-F	936	9765	HD 22.4 S3	0282
BLDL-vg	H07RN-F	H07RN-F	916	9765	HD 22.4 S3	0282
BDL-vg	H01N2-D	H01N2-D	916	9765	HD 22.6 S3	0282
BDL-vg	H01N2-E	H01N2-E	916	9767	HD 22.6 S3	0282
		(N)SHTÖU(SMK)		11178		0250
		(N)SHTÖU(SMK)		11178		0250
		(N)TSWÖU-J		11178		0250
		(N)TSCGEWÖU(SMK)		11178		0250
		(N)TSCGEWÖU(SB)		11178		0250
		MGG-DIN 89160				0261
		MGCC-DIN 89158				0261
		FMGCC-DIN 89159				
		YSLTK-JZ				0250